



**VIVAX**  
**METROTECH**

# Loc3-5Tx 5-Watt Transmitter

Technical Specifications V1.7



## Worldwide Locations

### World Headquarters, United States of America

**Vivax-Metrotech Corporation**

3251 Olcott Street, Santa Clara, CA 95054, USA

T/Free : 1-800-446-3392

Tel : +1-408-734-1400

Fax : +1-408-734-1415

Website : [www.vivax-metrotech.com](http://www.vivax-metrotech.com)

Email : [SalesUSA@vxmt.com](mailto:SalesUSA@vxmt.com)

### Central/South America and the Caribbean

**Ventas para América Latina**

3251 Olcott Street, Santa Clara, CA 95054, USA

T/Free : 1-800-446-3392

Tel : +1-408-734-1400

Fax : +1-408-743-5597

Website : [www.vivax-metrotech.com](http://www.vivax-metrotech.com)

Email : [LatinSales@vxmt.com](mailto:LatinSales@vxmt.com)

### Canada

**Vivax Canada, Inc.**

41 Courtland Ave Unit 8, Vaughan, ON L4K 3T3, Canada

Tel : +1-289-846-3010

Fax : +1-905-752-0214

Website : [www.vivax-metrotech.ca](http://www.vivax-metrotech.ca)

Email : [SalesCA@vxmt.com](mailto:SalesCA@vxmt.com)

### United Kingdom

**Vivax-Metrotech Ltd.**

Unit 1, B/C Polden Business Centre, Bristol Road, Bridgwater, Somerset, TA6 4AW, UK

Tel : +44(0)1793 822679

Website : [www.vivax-metrotech.co.uk](http://www.vivax-metrotech.co.uk)

Email : [SalesUK@vxmt.com](mailto:SalesUK@vxmt.com)

### France

**Vivax-Metrotech SAS**

Technoparc - 1 allée du Moulin Berger, 69130 Ecully, France

Tel : +33(0)4 72 53 03 03

Fax : +33(0)4 72 53 03 13

Website : [www.vivax-metrotech.fr](http://www.vivax-metrotech.fr)

Email : [SalesFR@vxmt.com](mailto:SalesFR@vxmt.com)

### Germany

**Metrotech Vertriebs GmbH**

Am steinernen Kreuz 10a  
D-96110 Schesslitz

Tel : +49 954 277 227 43

Website : [www.vivax-metrotech.de](http://www.vivax-metrotech.de)

Email : [SalesEU@vxmt.com](mailto:SalesEU@vxmt.com)

### China

**Vivax-Metrotech (Shanghai) Ltd.**

3/F No.90, Lane 1122 Qinzhou Rd.(N),  
Shanghai, China 200233

Tel : +86-21-5109-9980

Fax : +86-21-2281-9562

Website : [www.vivax-metrotech.com](http://www.vivax-metrotech.com)

Email : [SalesCN@vxmt.com.cn](mailto:SalesCN@vxmt.com.cn)

## A. Description and Typical Applications

Item	Parameter
Model Name	Loc3-5Tx
Model Number	VX219-05
Description	5-Watt Pipe & cable locator transmitter
Designed Use	<ul style="list-style-type: none"> <li>- Transmitting active signals for the location of buried pipes and cables</li> <li>- Transmitting a fault-find frequency for the detection of cable faults</li> </ul>

## B. Characteristics

Item	Parameter									
Construction	High-impact ABS plastic									
Weight	<ul style="list-style-type: none"> <li>- With Alkaline battery tray: 8.6lbs (3.9kg)</li> <li>- With Rechargeable battery tray: 7.15lbs (3.24kg)</li> </ul>									
Dimensions	13.1in(L) x 7.2in(W) x 7.3in(H) (332mm x 182mm x 185mm)									
Display Type	<ul style="list-style-type: none"> <li>- Monochrome-dot-matrix graphic LCD display with LED backlight</li> <li>- 2.4in x 1.3in (60mm x 32mm)</li> </ul>									
Power Options	<ul style="list-style-type: none"> <li>- 8 x alkaline "D" cells</li> <li>- 12~22V external DC power</li> <li>- Optional Li-Ion rechargeable battery tray</li> </ul>									
Battery Life	<table border="1"> <thead> <tr> <th>Output Power</th> <th>Alkaline</th> <th>Li-Ion (Rechargeable)</th> </tr> </thead> <tbody> <tr> <td>1-watt</td> <td>25 hours</td> <td>50 hours</td> </tr> <tr> <td>5-watt</td> <td>4 hours</td> <td>10 hours</td> </tr> </tbody> </table> <p>* Continuous use at 70°F (21°C) with the backlight activated. The battery life varies with temperature, battery type and quality. Recharging cycles are approximately 500 times the life cycle.</p>	Output Power	Alkaline	Li-Ion (Rechargeable)	1-watt	25 hours	50 hours	5-watt	4 hours	10 hours
Output Power	Alkaline	Li-Ion (Rechargeable)								
1-watt	25 hours	50 hours								
5-watt	4 hours	10 hours								
Environmental	IP54 and NEMA 4									
External Connectors	<ul style="list-style-type: none"> <li>- 1 x 3 pin connection socket (XLR)</li> <li>- 1 x fuse (output protection) 1.6A/250V</li> <li>- 1 x Mini-USB socket</li> <li>- 1 x socket for battery charger &amp; 12V DC power in</li> </ul>									
Temperature Range	<ul style="list-style-type: none"> <li>- Operating: -4°F to 122°F (-20°C to 50°C)</li> <li>- Storage: -40°F to 140°F (-40°C to 60°C)</li> </ul>									

<b>Compliance/Approvals</b>	<ul style="list-style-type: none"> <li>- Complies with European standard CE (Directive 99/5/EC) <ul style="list-style-type: none"> <li>• EN 55011</li> <li>• EN 61000-4-2: A1 &amp; A2</li> <li>• EN 61000-4-3</li> <li>• EN 61000-4-8: A1</li> <li>• ETSI EN 300 330-2</li> <li>• ETSI EN 301 489-1</li> <li>• ETSI EN 301 489-3</li> </ul> </li> </ul>	<ul style="list-style-type: none"> <li>- Complies with FCC rules part 15 <ul style="list-style-type: none"> <li>• CFR 47 part 2</li> <li>• CFR 47 part 15</li> </ul> </li> </ul>
<b>Manufacturing</b>	Designed and manufactured per ISO 9001:2015	
<b>What's In the Box</b>	<ul style="list-style-type: none"> <li>- Loc3-5Tx Transmitter</li> <li>- Direct Connection Leads (XLR plug with 10ft (3.5m) red/black leads)</li> <li>- Ground stake</li> <li>- Alkaline battery tray</li> <li>- 8 x D Cell alkaline batteries</li> </ul>	
<b>Compatible Accessories Options</b>	<ul style="list-style-type: none"> <li>- 2-inch (50mm) transmitter clamp</li> <li>- 4-inch (100mm) transmitter clamp</li> <li>- 5-inch (125mm) transmitter clamp</li> <li>- 18-inch (450mm) flexible transmitter clamp</li> <li>- Ground Extension Spool</li> <li>- Backpack</li> <li>- Live Plug Connector (LPC Separation Filter) - to connect and use the transmitter on lines carrying up to 240V AC</li> <li>- LCC Live Cable Connector - to connect and use the transmitter on lines carrying up to 480V AC</li> <li>- Rechargeable Battery Tray - custom Li-Ion battery tray and charger (input DC12V 3A, output DC18V-93.6 Wh)</li> <li>- 12V DC Vehicle Power Lead - for powering and charging the optional rechargeable battery from a vehicle</li> </ul>	

## C. Operational

Item	Parameter
<b>Information Displayed</b>	<ul style="list-style-type: none"> <li>- Current (numeric)</li> <li>- Volts</li> <li>- Resistance</li> <li>- Frequency of output signal</li> </ul>

	<ul style="list-style-type: none"> <li>- High voltage warning if volts online exceed 30V AC</li> <li>- Beeper volume (three levels &amp; off)</li> <li>- Battery condition icon</li> <li>- Bar graph showing the proportion of successfully applied signal</li> <li>- Animation icon confirming connection mode (Induction, Direct connection, Clamp)</li> <li>- Tx-Link status (if installed)</li> </ul>
<b>Transmitting Modes</b>	<ul style="list-style-type: none"> <li>- <b>Induction mode</b> – applies signal inductively using the internal antenna</li> <li>- <b>Direct connection mode</b> - applies signal directly to the cable by clipping one output lead to the cable, the other to an independent ground</li> <li>- <b>Clamp mode</b> – applies signal using an inductive clamp (aka toroid or coupler) that is placed around the target pipe or cable</li> </ul> <p>* Modes are automatically selected when accessories are plugged in. The default mode (no accessories) is Induction.</p>

### Transmitting Frequency by Mode

<b>Induction Mode</b>	Multiple induction frequencies between 8.19 kHz and 200 kHz
<b>Direct Connection Mode</b>	Available frequencies between 98Hz and 200 kHz with default frequencies of 512Hz, 8.19 kHz, 33 kHz, 65 kHz, 200 kHz
<b>Clamp Mode</b>	Available frequencies between 8.19 kHz and 200 kHz with default frequencies of 8.19 kHz, 33 kHz, 65 kHz, and 200 kHz
<b>Transmitting Mode Power Output</b>	In accordance with FCC part 15: <ul style="list-style-type: none"> <li>- <i>Frequencies under 45 kHz - 5 watts</i></li> <li>- <i>Frequencies over 45 kHz - 1 watt</i></li> </ul>
<b>Maximum Output Voltage</b>	50V RMS
<b>Maximum Output Current</b>	0.3A RMS constant current
<b>Output Protection</b>	Output protected against accidental momentary connection to up to 240V AC
<b>Audio Indication</b>	<ul style="list-style-type: none"> <li>- Connection quality – Increased beep rate indicates a better-applied signal</li> <li>- Beeps to confirm the selected action</li> </ul>
<b>Controls</b>	<ul style="list-style-type: none"> <li>- Use pushbuttons to select: <ul style="list-style-type: none"> <li>• On/Off</li> <li>• Frequency</li> <li>• Output level</li> <li>• Information (volts &amp; resistance) / Setting (volume, frequency &amp; multi-mode)</li> </ul> </li> </ul>
<b>Compatible Receivers</b>	vLoc3 series, vLoc 2 series, vLoc series, VM-510FFL+

## D. Rechargeable Battery Tray (optional accessory)

Item	Parameter
<b>Description</b>	Optional Li-Ion rechargeable battery tray with charger for Loc3 series transmitters
<b>Input/output</b>	<ul style="list-style-type: none"> <li>- Input DC 12V 3A</li> <li>- Output DC 18V-93.6 Wh</li> </ul>
<b>Battery Type</b>	Li-Ion battery
<b>Temperature Range</b>	<ul style="list-style-type: none"> <li>- Operating: 14°F to 140°F (-10°C to 60°C)</li> <li>- Storage: -4°F to 140°F (-20°C to 60°C)</li> <li>- Charging: 32°F to 113°F (0 °C to 45 °C)</li> </ul>
<b>Storage humidity</b>	≤ 75% RH
<b>Weight</b>	<ul style="list-style-type: none"> <li>- Battery Tray: 3.31lbs. (1.5kg)</li> <li>- Transmitter with battery tray: 7.1lbs. (3.2kg)</li> </ul>
<b>Dimension</b>	13.1in(L) x 7.2in(W) x 2.9in(H) (332mm x 182mm x 73mm)
<b>Shipping Weight</b>	4.6lbs (2.1kg) (Battery Tray)
<b>Shipping Dimension</b>	16.1in(L) x 10.2in(W) x 6.7in(H) (410mm x 260mm x 170mm)
<b>Warranty</b>	One Year

## E. Shipping and Packaging

Item	Parameter
<b>Shipping Weight</b>	<ul style="list-style-type: none"> <li>- With alkaline battery tray: 13.9lbs. (6.3kg)</li> <li>- With rechargeable battery tray: 12.3lbs. (5.6kg)</li> </ul>
<b>Shipping Dimension</b>	15.7in(L) x 11.8in(W) x 8.7in(H) (400mm x 300mm x 220mm)

## F. Warranty

Item	Parameter
<b>Warranty</b>	<ul style="list-style-type: none"> <li>- Two years (Transmitter with alkaline battery tray)</li> <li>- Extended warranty available</li> </ul>

Disclaimer: Product and accessory specification and availability information are subject to change without prior notice.